

Case A (106)

Casing for Ajax device

Compatibility	LineSplit Fibra LineProtect Fibra MultiRelay Fibra
Device installation	<p>Number of devices 1 To install more devices, select a model with a different number of slots:</p> <ul style="list-style-type: none">• Case B (175);• Case C (260);• Case D (430). <p>Plastic latches to secure a device Slide the latches to remove the device.</p> <p>Cable fasteners to hold the cables together with ties</p> <p>Plastic stoppers to protect the installed device During drilling, the drill bit rests on the Case stoppers.</p> <p>Bubble level To check the inclination angle of the mount during installation.</p> <p>Recesses for drilling Ø16 mm or Ø20 mm The drill bit is fixed in the recess and does not move during drilling. We recommend using a hole saw for plastic.</p> <p>Wider holes To ensure that the casing is installed correctly, even if there are errors during installation.</p>
Key features	<p>Tamper board Included in the Case complete set. The tamper board connects to the appropriate device connector and protects the installed device from sabotage.</p>

	<p>Rotate the device by 180° The device is fixed in two positions. You can turn it 180.</p> <p>Holding screws in the casing lid</p> <p>Rotate the lid by 180° The lid of Case A (106) can be rotated 180° during installation.</p> <p>Latches to secure the lid during installation The latches prevent the lid from falling off Case until it is secured with screws.</p>
Recommendations	The device is designed for indoor use only. Case is produced in several versions.
Product	<p>Dimensions 106 × 168 × 56 mm 4.17" × 6.61" × 2.20"</p> <p>Weight 186 g 6,56 oz</p> <p>Operating temperature range from -10 °C to +40 °C from 14 °F to 104 °F</p> <p>Operating humidity up to 75%</p> <p>Protection class IP20</p>
Colours	Black White
Complete set	Case A (106) Tamper board Installation kit Quick start guide
Warranty	24 months